

Pegasus Wall Light

3D MODEL DESCRIPTION

Ride to the realm of dreams on the world's greatest stallion light!

- **This STL file is recommended for FDM Printers!**
- **3D Printing Time: 18 Hours 33 Minutes**
- **Approximately Height : 19,2 cm**

3D PRINT FILE SETTINGS (FOR 0.4 MM NOZZLE)

- **Line Width/ Nozzle:** 0.4 mm
- **First Layer Line Width:** 0.48 mm / 120%
- **Average Speed:** 20mm/s (First Layer) / 50 mm/s (All the other layers) | 20 mm/s (First Layer) / 500 mm/s (All the other layers on Bambu Lab)
- **Recommended Initial Layer Height:** 0.12 mm
- **Recommended Layer Height:** 0.12 mm
- **Recommended Perimeters/ Walls:** 3.
- **Recommended Infill (%):** 10% (Gyroid)
- **Needs Support:** No.
- **Build Plate Adhesion:** Skirt.

The parameters above are recommendations made by our staff; if you prefer, you can adapt them according to your preferences.

Happy Printing!

Pegasus Wall Light

Ride to the realm of dreams on the world's greatest stallion light!

Your Pegasus requires some assembly.

Follow the instructions below:

What you'll need:

Printed light LED Module (2x)

Battery Holder 12V On-Off

Switch

Solder

Soldering Iron

Electric Wire (5cm)



Pegasus Wall Light

On-off Switch (15mm x 10mm 12V)

(https://www.amazon.com/Endlessparts-Pieces-Black-Rocker-switch/dp/B09885NWGC/ref=sr_1_3?crid=26CUL3Y5FPNQE&keywords=switch+12v+15mm&qid=1690546495&srefix=switch+12v+15mm%2Caps%2C200&sr=8-3)

Battery Holder 23A

https://www.amazon.com/LUORNG-10PCS-Battery-Holder-Leads/dp/B09L87S74L/ref=sr_1_1_sspa?crid=OIAG6FT3G4J9&keywords=23a+battery+holder&qid=1689093789&srefix=23a+%2Caps%2C245&sr=8-1-spons&sp_csd=d2lkZ2V0TmFtZT1zcF9hdGY&psc=1

Wire

https://www.amazon.com/TYUMEN-Electrical-Extension-Flexible-Lighting/dp/B07SG23DT1/ref=sr_1_14_sspa?keywords=led+wire&qid=1690517964&sr=8-14-spons&sp_csd=d2lkZ2V0TmFtZT1zcF9hdGY&psc=1


LED Module

https://www.amazon.com/Rextin-Waterproof-Decorative-Advertising-Adhesive/dp/B07BKT53ZP/ref=sr_1_4_sspa?keywords=led%2Bmodules&qid=1689093544&sr=8-4-spons&sp_csd=d2lkZ2V0TmFtZT1zcF9hdGY&th=1

Pegasus Wall Light

Instructions:

Separate the LED modules from the rest. Do not cut the wires between these two modules.



On the end of one module, separate the two wires (the white and the red) from one another. Cut both wires at a length of 9cm. Strip the ends of both wires in about 1cm.



Pegasus Wall Light

Instructions:

Using a solder, attach the white wire to the battery holder on its negative side (the one with the spring).




Cut a separate piece of electric wire of 09cm, strip the ends and solder one of them to the positive side of the battery holder



Pegasus Wall Light

Instructions:

Thread the red wire through the rectangle hole on the Pegasus, then solder its end to the “o” (off) pin of the on-off switch.



Fit the on-off switch into the rectangle hole made for it on the Pegasus, and solder the wire connected to the “I” (on) pin of the on-off switch to the positive side of the battery holder.



Pegasus Wall Light

Instructions:

Use double sided tape to stick the battery holder in place inside the Pegasus according to the picture.



Using their own double sided tape, stick the two LED modules on the inside of the Pegasus on its designated place next to the openings on the model, according to the picture.



Wall Light DC Powered 12V Plug

ASSEMBLY DESCRIPTION

Your model requires some assembly. Follow the instructions below:

What you'll need:

Printed model
LED Module (depending on the model you're building - 2x or 4x)
DC Power Jack Female
On-Off Switch
Solder
Soldering Iron
Electric Wire 30cm

SUGGESTED LINKS FOR PARTS AND PIECES

On-off Switch (15mm x 10mm 12V)

[Amazon.com: Endlessparts 6 Pieces Black Rocker switch 15mm x 10mm 6a 2pin mini on off spst kdc1 12v b22](#)

DC Power Jack Female

[Amazon.com: ThreeBulls 12 Pieces 5.5mmx2.1mm 2 Pins DC Power Jack Female Panel Mounting Connector Socket](#)

Wire

[TYUMEN 100FT 16 Gauge 2pin 2 Color Red Black Cable Hookup Electrical Wire LED Strips Extension Wire 12V/24V DC Cable, 16AWG Flexible Wire Extension Cord for LED Ribbon Lamp Tape Lighting - Amazon.com](#)

LED Module


[REXTiN Super Bright 200pcs Mini 2835 2 LED Module DC12V Waterproof Decorative Light for Letter Sign Advertising Signs with Tape Adhesive Backside \(White\) - Amazon.com](#)

Wall Light DC Powered 12V Plug


3D MODEL DESCRIPTION

Instructions:

- Separate the LED modules from the rest. Do not cut the wires between these two modules.



- On the end of one module, separate the two wires (the white and the red) from one another. Cut both wires at a length of 9cm. Strip the ends of both wires in about 0,5cm.




Wall Light DC Powered 12V Plug


3D MODEL DESCRIPTION

Instructions:


- Cut 2 separate pieces of electric wire to use as POSITIVE (smaller) and NEGATIVE (bigger), strip the ends of both wires approximately 7mm.



- Use solder to attach the **positive** stripped wire end to the "I" (on) pin on the on-off switch.
- Now use solder to attach the **negative** stripped wire end to the "O" (off) pin on the on-off switch.




- place the wires through the hole and pass the negative wire through the hole for the DC power jack female.





Wall Light DC Powered 12V Plug

- Use solder to attach the **negative** stripped wire end to the small pin on the DC Power Jack female
- Now pass the negative LED module wire through the DC Plug hole and weld to the DC Power jack female pin.
- Fit the DC Power Jack female to the printed model



Wall Light DC Powered 12V Plug

- Weld the positive wire ("I" on) coming from the on-off switch to the positive wire in the LED module



- Use double sided tape to stick the 2 LED Modules on its designated place (Read Me File 1) on the printed model (read File 1)



- Your model is ready to **shine!**

